



Piston-Vibrators FP

Pneumatic piston vibrators for linear vibration with unlimited fine-tuning facilities for amplitude and frequency. Wide range.

Properties

- Quiet and efficient
- Rated frequency 1'800 – 9'300 vpm
- Force 32 – 6'150 N
- Continuously variable
- Can be used up to 120 °C, HT version up to 150 °C and LT version on request
- Resistant to extreme environmental conditions
- Also available with ATEX certification

Field of application

- Driving conveyor and discharge chutes
- Loosening or compacting of bulk materials
- Starting up of mechanical processes
- Filling facilities


Construction

Aluminium housing surface-hardened and corrosion-resistant

Technical data (with PSI, LBS, CF: www.findeva.com)

| Model | Vibrations 1000 vpm | | Force N | | air consumption l/min | | A Length mm | B SW mm | C Thread | D Inlet | E Outlet | Weight g |
|---------|------------------------|-------|------------|-------|--------------------------|-------|-------------------|---------------|-------------|------------|---------------------|-------------|
| | 2 bar | 6 bar | 2 bar | 6 bar | 2 bar | 6 bar | | | | | | |
| FP-12-S | 6,2 | 9,3 | 34 | 92 | 0,8 | 25 | 71 | 34 | M-8 | 1/8" | 1/8" | 153 |
| FP-12-M | 5 | 6,7 | 34 | 74 | 0,5 | 19 | 81 | 34 | M-8 | 1/8" | 1/8" | 178 |
| FP-12-L | 4 | 5,4 | 32 | 81 | 1 | 20 | 94 | 34 | M-8 | 1/8" | 1/8" | 212 |
| FP-18-S | 5 | 7,7 | 66 | 187 | 5 | 57 | 81 | 42 | M-10 | 1/8" | 1/8" | 300 |
| FP-18-M | 4 | 5,9 | 68 | 188 | 4 | 52 | 94 | 42 | M-10 | 1/8" | 1/8" | 352 |
| FP-18-L | 3,1 | 4,6 | 64 | 206 | 5 | 46 | 109 | 42 | M-10 | 1/8" | 1/8" | 423 |
| FP-25-S | 3,6 | 5,5 | 126 | 416 | 13 | 93 | 98 | 50 | M-12 | 1/8" | 1/4" | 553 |
| FP-25-M | 3 | 4,2 | 142 | 504 | 23 | 87 | 116 | 50 | M-12 | 1/8" | 1/4" | 672 |
| FP-25-L | 2,4 | 3,7 | 186 | 594 | 18 | 93 | 136 | 50 | M-12 | 1/8" | 1/4" | 820 |
| FP-35-S | 3,8 | 5,8 | 294 | 1038 | 23 | 162 | 98 | 65 | M-12 | 1/4" | 1/4" | 926 |
| FP-35-M | 3 | 4,6 | 248 | 1080 | 24 | 141 | 116 | 65 | M-12 | 1/4" | 1/4" | 1135 |
| FP-35-L | 2,4 | 3,6 | 282 | 1066 | 38 | 135 | 136 | 65 | M-12 | 1/4" | 1/4" | 1382 |
| FP-50-M | 1,85 | 2,8 | 490 | 1660 | 48 | 192 | L 154 | A 90 | C 8,8 | F 1 1/4" | F ₁ 1/4" | 3300 |
| FP-60-M | 1,95 | 2,7 | 610 | 2170 | 90 | 275 | L 154 | A 110 | C 8,8 | F 1 1/4" | F ₁ 3/8" | 4250 |
| FP-95-M | 1,8 | 2,8 | 1620 | 6150 | 170 | 490 | L 156 | A 150 | C 13,0 | F 3/8" | F ₁ 3/8" | 9460 |

FP-50 – 95



Housing made from hard-anodized aluminium alloy
Piston made from leaded-bronze
Steel spring starting device
Hard anodized aluminium end cap

FP-12 – 35

